

# IR18.D10L-F60.GP1I.7BF

Article number: 11193949

### Overview

- distance measuring
- 0 ... 10 mm
- push-pull
- IO-Link
- connector M12
- -25 ... 75 °C
- IP 67



Picture similar





Technical data	
General data	
Mounting type	Flush
Special type	Linearized
Туре	Distance measuring
Measuring distance Sd	0 10 mm
Resolution	< 0.005 mm (High Accuracy Mode)
Repeat accuracy	0.015 mm
Adjustment	IO-Link
Teach	Single point, Two point, Window
Linearity error	± 40 μm (S = 0 8 mm) ± 160 μm (S = 0 10 mm)
Temperature drift	±3% (Full Scale)
Hysteresis	< 99 % (adjustable)
Power on indication	LED green
Output indicator	LED yellow
Electrical data	
Response time (factory characteristic)	< 1 ms
Switching frequency	800 Hz
Voltage supply range +Vs	8 36 VDC
Current consumption max. (no load)	15 mA
Output circuit	Push-pull IO-Link
Output current	100 mA
Short circuit protection	Yes

Electrical data	
Reverse polarity protection	Yes
Mechanical data	
Design	Cylindrical threaded
Material (sensing face)	PBT
Housing material	Brass nickel plated
Dimension	18 mm
Housing length	60 mm
Connection types	Connector M12
Tightening torque max.	40 Nm
Ambient conditions	
Operating temperature	-25 +75 °C
Protection class	IP 67
Communication interface	
Interface	IO-Link V1.1
Baud rate	230,4 kBaud (COM 3)
Cycle time	≥ 0.6 ms
Process data length	32 Bit
Process data structure	Bit 0 = SSC1 (distance) Bit 1 = SSC2 (distance) Bit 3 = alarm Bit 4 = SSC3 (frequency) Bit 5 = SSC4 (counter) Bit 16-31 = 16 Bit measurement
IO-Link port type	Class A



# IR18.D10L-F60.GP1I.7BF

Article number: 11193949

### **Technical data**

### **Communication interface**

Adjustable parameters

Measuring range Switching point Switching hysteresis Measured value filtering

Time filters

LED status indicators Output logic

Output logic
Output circuit
Counter

Deactivate the sensor element

Find Me function

#### Communication interface


Additional data


Distance
Frequency
Operating cycles
Operating hours
Boot cycles
Operating voltage
Device temperature

Histograms


# **Dimension drawing**

# Pin assignment





# Connection diagram



# Resolution

