

# IR18.P12S-F50.PC1Z.7BCV

Inductive proximity switch - large sensing distance

Article number: 11149166

#### Overview

- 12 mm
- PNP break function (NC)
- cable, 2 m
- -25 ... 75 °C
- IP 67



Picture similar







Technical data	
General data	
Mounting type	Flush
Special type	Enhanced distance (GammaProx)
Nominal sensing distance Sn	12 mm
Temperature drift	± 10 %
Hysteresis	3 20 % of Sr
Output indicator	LED red
Correction factor typ.	Mild steel 100 %, stainless steel 70 %, aluminum 40 %
Electrical data	
Switching frequency	< 400 Hz
Voltage supply range +Vs	6 36 VDC
Current consumption max. (no load)	10 mA
Output circuit	PNP break function (NC)

Electrical data	
Voltage drop Vd	< 2 VDC
Output current	< 100 mA
Short circuit protection	Yes
Reverse polarity protection	Yes
Mechanical data	
Туре	Cylindrical threaded
Material (sensing face)	PBT
Housing material	Brass nickel plated
Dimension	18 mm
Housing length	50 mm
Connection types	Cable, 2 m
Tightening torque max.	40 Nm
Ambient conditions	
Operating temperature	-25 +75 °C
Protection class	IP 67

#### Remarks


Increased sensing distance

# IR18.P12S-F50.PC1Z.7BCV


Inductive proximity switch - large sensing distance

Article number: 11149166


#### **Dimension drawing**




## Connection diagram



#### Correction factors for different mounting situation (approx.)



Mounting material	Correction factor
Mild steel	100 %
Stainless steel	100 %
Aluminum	100 %



Mounting material	Correction factor
Mild steel	105 %
Stainless steel	95 %
Aluminum	95 %



Mounting material	Correction factor
Mild steel	not possible
Stainless steel	110 %
Aluminum	65 %



# IR18.P12S-F50.PC1Z.7BCV

Inductive proximity switch - large sensing distance

Article number: 11149166

## **Mounting instructions**

